固件升级失败的 Discovery 恢复方法 iOS 版

注意事项:	2
步骤 1:下载安装蓝牙芯片公司 Nordic 提供的工具软件 nRF ToolBox	2
步骤 2:用 QQ 接收固件升级用的文件,选择用 nRF Toolbox 打开文件。	3
步骤 3:在 DFU 功能中选择刚才接收到的固件升级文件。	3
步骤 4:连接 Discovery 主机。	4
步骤 5:点击 Upload,等待升级完成。	5

SHOULEU

注意事项:

- (1) 无需着急,只要能进入固件升级模式,就一定能恢复。
- (2) 本方法适用于 Discovery 码灯在空中固件升级时异常中断后的恢复。此时 Discovery 主机界面上显示 "DFU START …"。



- (3) 本方法适用于 iOS 系统的 iPhone、iPad。
- (4) 对 Discovery 进行恢复时,请尽量把手机和 Discovery 主机靠近。

步骤 1:下载安装蓝牙芯片公司 Nordic 提供的工具软件 nRF ToolBox

在 App Store 搜索 nRF Toolbox,并安装。



SHOULEU

步骤 2:用 QQ 接收固件升级用的文件,选择用 nRF Toolbox 打开文件

在 QQ 中接收.zip 后缀名的固件升级文件 ;文件收下来后点击 "用其他应用" 打开 ;选择在 "nRF Toolbox" 中打开。



步骤 3 : 在 DFU 功能中选择刚才接收到的固件升级文件







步骤 4:连接 Discovery 主机

○ 中国移动 [•] Back	er 09:53 er er og 19:53 er	' * 68% = D	•••••• p	·国移动 ᅙ	10:01 Select Device	1 ∦ 58% ■		••••••	○ 中国移动 Back	↔ 10:02 Bluetooth*	
	DEFAULT DFU		(î	Shanren	DFU					ShanrenDFU	
	FIRMWARE			lodestone	e					FIRMWARE	
Name: Size:	Discovery-V2.0.4-CN.zip 97117 bytes			lodestone	e				Name: Size:	Discovery-V2.0.4-CN.zip 97117 bytes	
Туре:	Distribution packet (ZIP)		•	lodeston	e			TE	Туре:	Distribution packet (ZIP)	
	DEVICE FIRMWARE UPDATE			No name	1			PD/		DEVICE FIRMWARE UPDATE	
))	Upload			No name	I			КE U		Upload	
			· •	lodeston	e		_	WAF			
	DFU Library version 3.0.6			Apple TV	,			IRM		DFU Library ver	sio
				Discover	у						
								EVIC			
[SELECT DEVICE Wireless by Nordic									SELECT DEVICE Wireless by Nordic	
)点击	SELECT DEVI	CE	(2	2)选择	Shanren	DFU			(3)Upload 变蓝	

SHOULEU

步骤 5:点击 Upload,等待升级完成

•••••• 中国移动 名 く Back		10:02Bluetooth'	≁ ∦ 58% = ⊃ (Ì		••••••	中国移动 ack	10:02Bluetooth	≁ ¥ 58% ■ (j	≁ ¥ 58% ■⊃ (Ì		◎ 中国移动 ack	10:03Bluetooth	≁ ∦ 58% ■ (Ì	
DEVICE FIRMWARE UPDATE		ShanrenDFU					ShanrenDFU	anrenDFU	DEFAULT DFU					
	Name: Size: Type:	Discovery-V2.0.4-CN.zip 97117 bytes Distribution packet (ZIP)		6	DEVICE FIRMWARE UPDATE	Name: Size: Type:	Discovery-V2.0.4-CN.zi 97117 bytes Distribution packet (ZIF	zip P)		E	Name: Size: Type:	Discovery-V2.0.4-CN.z 97117 bytes Distribution packet (ZI	ip P)	
		Select File DEVICE FIRMWARE UPDATE Upload					Select File DEVICE FIRMWARE UPDA Cancel Uploading 2% (1/1)	TE	\Rightarrow	NARE UPDAT		Select File		
		DFU Library ver	sion 3.0.6				DFU Library v	ersion 3.0.6		DEVICE FIRM			rersion a.0.6	
		Wireless by Nordic					Wireless by Nordic					Wireless by Nordic		
(1)点击 Upload					(2)出现进度条					(3)升级完成				

升级完成后, Discovery 屏幕显示恢复正常。



注意:如果在点击 Upload 之前, App 和 Discovery 之间的连接断开了,点击"SELECT DEVICE",重复步骤 4~步骤 5,完成 Discovery 的升级